

FORM PCT-1390
(REV 10-2000)

U.S. DEPARTMENT OF COMMERCE PATENT AND TRADEMARK OFFICE

ATTORNEY'S DOCKET NUMBER

41253

**TRANSMITTAL LETTER TO THE UNITED STATES
DESIGNATED/ELECTED OFFICE (DO/EO/US)
CONCERNING A FILING UNDER 35 U.S.C. 371**

U.S. APPLICATION NO. (If known, see 37 CFR 1.5)

09/830447INTERNATIONAL APPLICATION NO.
PCT/GB00/02104INTERNATIONAL FILING DATE
1 June 2000PRIORITY DATE CLAIMED
1 June 1999

TITLE OF INVENTION Improvements in Radio Positioning Systems

APPLICANT(S) FOR DO/EO/US

Peter James DUFFETT-SMITH, James Paul BRICE and Paul HANSEN

Applicant herewith submits to the United States Designated/Elected Office (DO/EO/US) the following items and other information:

1. ☒ This is a **FIRST** submission of items concerning a filing under 35 U.S.C. 371.
2. ☐ This is a **SECOND** or **SUBSEQUENT** submission of items concerning a filing under 35 U.S.C. 371.
3. ☒ This is an express request to promptly begin national examination procedures (35 U.S.C. 371(f)).
4. ☒ The US has been elected by the expiration of 19 months from the priority date (PCT Article 31).
5. ☒ A copy of the International Application as filed (35 U.S.C. 371(c)(2))
 - a. ☒ is attached hereto (required only if not communicated by the International Bureau).
 - b. ☒ has been communicated by the International Bureau.
 - c. ☐ is not required, as the application was filed in the United States Receiving Office (RO/US).
6. ☐ An English language translation of the International Application as filed (35 U.S.C. 371(c)(2)).
7. ☒ Amendments to the claims of the International Application under PCT Article 19 (35 U.S.C. 371(c)(3))
 - a. ☐ are attached hereto (required only if not communicated by the International Bureau).
 - b. ☐ have been communicated by the International Bureau.
 - c. ☐ have not been made; however, the time limit for making such amendments has NOT expired.
 - d. ☒ have not been made and will not be made.
8. ☐ An English language translation of the amendments to the claims under PCT Article 19 (35 U.S.C. 371(c)(3)).
9. ☒ An oath or declaration of the inventor(s) (35 U.S.C. 371(c)(4)).
10. ☐ An English language translation of the annexes to the International Preliminary Examination Report under PCT Article 36 (35 U.S.C. 371(c)(5)).

Items 11 to 16 below concern document(s) or information included:

11. ☐ An Information Disclosure Statement under 37 CFR 1.97 and 1.98.
12. ☒ An assignment document for recording. A separate cover sheet in compliance with 37 CFR 3.28 and 3.31 is included.
13. ☒ A FIRST preliminary amendment.
☐ A SECOND or SUBSEQUENT preliminary amendment.
14. ☐ A substitute specification.
15. ☐ A change of power of attorney and/or address letter.
16. ☒ Other items or information:
 - (a) Copy of International Search Report (12 September 2000).
 - (b) Copy of Published International Application (7 December 2000).
 - (c) Copy of Demand (18 December 2000).
 - (d) Copy of Notification of Receipt of Demand (16 January 2001).

U.S. APPLICATION NO (if known) 097/830447 INTERNATIONAL APPLICATION NO PCT/GB00/02105

ATTORNEY'S DOCKET NUMBER
4125217. ☒ The following fees are submitted:**BASIC NATIONAL FEE (37 CFR 1.492 (a) (1) - (5)) :**Neither international preliminary examination fee (37 CFR 1.482)
nor international search fee (37 CFR 1.445(a)(2)) paid to USPTO
and International Search Report not prepared by the EPO or JPO \$1000.00International preliminary examination fee (37 CFR 1.482) not paid to
USPTO but International Search Report prepared by the EPO or JPO \$860.00International preliminary examination fee (37 CFR 1.482) not paid to USPTO but
international search fee (37 CFR 1.445(a)(2)) paid to USPTO \$710.00International preliminary examination fee paid to USPTO (37 CFR 1.482)
but all claims did not satisfy provisions of PCT Article 33(1)-(4) \$690.00International preliminary examination fee paid to USPTO (37 CFR 1.482)
and all claims satisfied provisions of PCT Article 33(1)-(4) \$100.00**ENTER APPROPRIATE BASIC FEE AMOUNT =****CALCULATIONS** PTO USE ONLY

\$ 860.00

Surcharge of \$130.00 for furnishing the oath or declaration later than ☐ 20 ☐ 30
months from the earliest claimed priority date (37 CFR 1.492(e)).

\$ 0.00

CLAIMS	NUMBER FILED	NUMBER EXTRA	RATE
Total claims	26 - 20 =	6	X \$18.00
Independent claims	4 - 3 =	1	X \$80.00
MULTIPLE DEPENDENT CLAIM(S) (if applicable)			+ \$270.00

\$ 108.00

\$ 80.00

\$ 270.00

TOTAL OF ABOVE CALCULATIONS =

\$ 1318.00

☐ Applicant claims small entity status. See 37 CFR 1.27. The fees indicated above
are reduced by 1/2.

\$ (0.00)

SUBTOTAL =

\$ 1318.00

Processing fee of \$130.00 for furnishing the English translation later than ☐ 20 ☐ 30
months from the earliest claimed priority date (37 CFR 1.492(f)).

\$ 0.00

TOTAL NATIONAL FEE =

\$ 1318.00

Fee for recording the enclosed assignment (37 CFR 1.21(h)). The assignment must be
accompanied by an appropriate cover sheet (37 CFR 3.28, 3.31). \$40.00 per property

\$ 40.00

TOTAL FEES ENCLOSED =

\$ 1358.00

Amount to be
refunded:
charged:

\$

\$

a. ☒ A check in the amount of \$ 1358.00 to cover the above fees is enclosed.b. ☐ Please charge my Deposit Account No. _____ in the amount of \$ _____ to cover the above fees.
A duplicate copy of this sheet is enclosed.c. ☒ The Commissioner is hereby authorized to charge any additional fees which may be required, or credit any
overpayment to Deposit Account No. 18-2220. A duplicate copy of this sheet is enclosed.**NOTE: Where an appropriate time limit under 37 CFR 1.494 or 1.495 has not been met, a petition to revive (37 CFR 1.137(a) or (b)) must be filed and granted to restore the application to pending status.**

SEND ALL CORRESPONDENCE TO

Roylance, Abrams, Berdo & Goodman, L.L.P.
1300 19th Street, N.W., Suite 600
Washington, D.C. 20036

(202) 659-9076

SIGNATURE

John E. Holmes

NAME

29.392

REGISTRATION NUMBER

41253

PATENT

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

In re Application of:	:	
	:	
Peter James DUFFETT-SMITH et al.	:	Group Art Unit:
	:	
Serial No.: Not yet assigned	:	Examiner:
	:	
Filed: Herewith	:	
	:	
For: Improvements in Radio Positioning Systems	:	

PRELIMINARY AMENDMENT

COMMISSIONER FOR PATENTS
Washington, D.C. 20231

Sir:

This application is the U.S. national stage under 35 U.S.C. § 371 of International Application No. PCT/GB00/02104, filed June 1, 2000. Prior to the first examination on the merits, please amend this application as follows:

IN THE CLAIMS:

Please amend claims 6, 7 and 13-15 as follows:

6. (Amended) A radio positioning method according to claim 3, wherein the step of acquiring data from said one or more receivers includes instigating acquisition of said data from a common location.
7. (Amended) A radio positioning method according to claim 3, wherein the step of acquiring data from said one or more receivers includes instigating acquisition of said data from each said receiver at times determined by each said receiver.
13. (Amended) A radio positioning system according to claim 10, wherein the means for acquiring data from said one or more receivers includes a computer system arranged to instigate the transfer of said data from said one or more receivers to said computer system at times determined by said computer system.


14. (Amended) A radio positioning system according to claim 10, wherein the means for acquiring data from said one or more receivers includes a computer system, and including means for instigating said acquisition of data from each said receiver at times determined by each said receiver.

15. (Amended) A digital telephone network, including a radio positioning system according to claim 10.

REMARKS

Claims 1-15 are pending in this application. Of these, dependent claims 6, 7 and 13-15 have been amended to remove improper multiple dependencies. Early and favorable action on the merits of this application is respectfully requested.

Respectfully submitted,



John E. Holmes
Attorney for Applicants
Reg. No. 29,392

Roylance, Abrams, Berdo & Goodman
1300 19th Street, N.W., Suite 600
Washington, D.C. 20036-2680
(202) 659-9076

Dated: April 27, 2001

MARKED UP VERSION TO SHOW CHANGES MADE

6. (Amended) A radio positioning method according to [any of claims 3 to 5] claim 3, wherein the step of acquiring data from said one or more receivers includes instigating acquisition of said data from a common location.

7. (Amended) A radio positioning method according to [any of claims 3 to 5] claim 3, wherein the step of acquiring data from said one or more receivers includes instigating acquisition of said data from each said receiver at times determined by each said receiver.

13. (Amended) A radio positioning system according to [any of claims 10 to 12] claim 10, wherein the means for acquiring data from said one or more receivers includes a computer system arranged to instigate the transfer of said data from said one or more receivers to said computer system at times determined by said computer system.

14. (Amended) A radio positioning system according to [any of claims 10 to 13] claim 10, wherein the means for acquiring data from said one or more receivers includes a computer system, and including means for instigating said acquisition of data from each said receiver at times determined by each said receiver.

15. (Amended) A digital telephone network, including a radio positioning system according to [any of claims 10 to 14] claim 10.

093044 04204
T0340 440360

IMPROVEMENTS IN RADIO POSITIONING SYSTEMS

5 The present invention relates generally to improvements in radio positioning systems and their methods of operation and, more particularly, to methods and apparatus for simplifying the acquisition of data required in such systems.

10 EP-A-0 303 371, the contents of which are hereby incorporated by reference, describes a radio navigation and tracking system which makes use of independent radio transmitters set up for other purposes. The signals from each transmitter, taken individually, are received by two receiving stations, one at a fixed and known location, and the other mounted on the mobile object whose position is to be determined. A representation of the signals received at one receiving station is sent via a link to a processor at the other receiving station, where the received signals are compared to find their phase differences or time delays. Three such measurements, made on three
15 widely spaced independent transmitters, are sufficient to determine the position of the mobile receiver in two dimensions, i.e. its position on the ground. The phase or time offset between the master oscillators in the two receivers is also determined.

20 "CURSOR", as the system described in EP-A-0 303 371 is known, is a radio positioning system which can use the signals radiated by existing non-synchronised radio transmitters to locate the position of a portable receiver. Unlike some other systems which use the temporal coherence properties of networks of purpose-built synchronised transmitters, CURSOR makes use of the spatial coherence of the signals transmitted by single transmitters. In a further development (see EP-A-0 880 712 &
25 WO-A-99/21028), the technology has been applied to find the position of a mobile phone handset in a GSM or other digital telephone system, and these are examples of an 'Enhanced Observed Time Difference' (E-OTD) method using the down-link signals radiated by the network of Base Transceiver Stations (BTS) of the telephone system.

30

In the digital mobile telephone application described in EP-A-0 880 712, the contents of which are hereby incorporated by reference, the signals from each BTS within range of the handset are received both by the handset itself and by a fixed nearby receiver, the Location Measurement Unit (LMU), whose position is accurately known.

Representations of the received signals are passed to a Mobile Location Centre (MLC) where they are compared in order to find the time difference between them. Figure 1 shows the geometry of a standard two-dimensional system. The origin of Cartesian co-ordinates x and y is centred on the LMU positioned at O. The orientation of the axes is immaterial, but may conveniently be set so that the y axis lies along the north-south local map grid. The handset, R, is at vector position \mathbf{r} with respect to the LMU position O. A BTS, A, is shown at vector position \mathbf{a} .

Consider first the signals from BTS A. The time difference, Δt_a , measured between the signals received at R and O is given by

$$\Delta t_a = (|\mathbf{r} - \mathbf{a}| - |\mathbf{a}|) / \nu + \varepsilon ,$$

where ν is the speed of the radio waves, ε is the clock time offset between the clocks in the receivers at R and O, and the vertical bars each side of vector quantities denote that it is the magnitude of the vectors which are used in the equation. The value of ε represents the synchronisation error between the measurements made by the two receivers. Similarly, may be written for two other BTSs (B and C) at vector positions \mathbf{b} and \mathbf{c} (not shown):

$$\Delta t_b = (|\mathbf{r} - \mathbf{b}| - |\mathbf{b}|) / \nu + \varepsilon ,$$

$$\Delta t_c = (|\mathbf{r} - \mathbf{c}| - |\mathbf{c}|) / \nu + \varepsilon . \quad (1)$$

The values of Δt_a , Δt_b , Δt_c , are measured by the methods disclosed in EP-A-0 880 712 and the values of \mathbf{a} , \mathbf{b} , \mathbf{c} , and ν are known. Hence the equations (1) can be solved to find the position of the handset, \mathbf{r} , together with the value of ε .

In WO-A-99/21028, the contents of which are hereby incorporated by reference, it is described how these same time offsets can be measured using locally-created *templates* in a GSM telephone system as follows. Suppose that the handset R has recorded a short burst of the GSM signals from BTS A. Contained within that recording is the framing structure, synchronisation bursts and other 'given' data (or

predetermined values) which are a constant feature of those transmissions. The processor within the handset can create a matching template, based on the known structure of the network signals. Received signals can then be matched by the locally-generated template. When the template finds a match, the correlation peak at the position of best match corresponds to the time offset between the received signals and the local clock inside the handset. For the signals radiated by BTS A this measured time offset, Δt_{a1} , is given by

$$\Delta t_{a1} = (|\mathbf{r} - \mathbf{a}|)/\nu + \alpha_a + \varepsilon_1 ,$$

where α_a is the time offset of the BTS transmissions and ε_1 is the time offset of the handset's internal clock, both relative to an imaginary universal 'absolute' clock. The signals from BTSs B and C may also be measured in the same way, giving

$$\Delta t_{b1} = (|\mathbf{r} - \mathbf{b}|)/\nu + \alpha_b + \varepsilon_1 ,$$

and

$$\Delta t_{c1} = (|\mathbf{r} - \mathbf{c}|)/\nu + \alpha_c + \varepsilon_1 . \quad (2)$$

The same measurements can also be made by the LMU, giving

$$\Delta t_{a2} = (|\mathbf{a}|)/\nu + \alpha_a + \varepsilon_2 ,$$

$$\Delta t_{b2} = (|\mathbf{b}|)/\nu + \alpha_b + \varepsilon_2 ,$$

and

$$\Delta t_{c2} = (|\mathbf{c}|)/\nu + \alpha_c + \varepsilon_2 , \quad (3)$$

where ε_2 is the time offset of the LMU's internal clock relative to the same imaginary universal absolute clock. Subtracting equations 3 from equations 2 gives

$$\Delta t_a = \Delta t_{a1} - \Delta t_{a2} = (|\mathbf{r} - \mathbf{a}| - |\mathbf{a}|)/\nu + \varepsilon,$$

$$\Delta t_b = \Delta t_{b1} - \Delta t_{b2} = (|\mathbf{r} - \mathbf{b}| - |\mathbf{b}|)/\nu + \varepsilon,$$

5 and

$$\Delta t_c = \Delta t_{c1} - \Delta t_{c2} = (|\mathbf{r} - \mathbf{c}| - |\mathbf{c}|)/\nu + \varepsilon, \quad (4)$$

10 where $\varepsilon = \varepsilon_1 - \varepsilon_2$. It will be noted that equations 4 are just like equations 1, and can be solved in the same way to find the position of the handset, \mathbf{r} , and the value of ε .

It will be apparent that the CURSOR method as described above, in common with all other methods which use the signals from non-synchronised transmitters, requires a network of LMUs to be set up within the coverage area of the telephone system.

15 These units act as reference points at which the unsynchronised signals radiated by the BTSs are measured for comparison with the same signals received by a handset. Each position measurement requires a match to be made between the signals received by the handset from a number of nearby BTSs, and signals received by an LMU from the same set of BTSs. In practice, it is often difficult to find a match using just one LMU,

20 especially if the LMU network is sparse, since the handset may receive signals from BTSs not received by the LMU, and *vice-versa*. It is therefore necessary to combine the measurements from two or more LMUs. However, each new LMU brought into the calculation adds a further unknown clock time offset ($\varepsilon_2, \varepsilon_3$ etc.), each of which therefore requires an additional BTS measurement to provide the extra equation

25 needed to solve for all the unknown quantities.

One solution to this problem is presented in WO-A-99/21028 where it is shown how the LMU network can be synchronised. Referring to Figure 2, suppose that an adjacent pair of LMUs, U_1 and U_2 , can see a common BTS. The positions of the

30 LMUs and the BTS are all known, so a single measurement of the BTS signals by each LMU is sufficient to determine the clock time offset between the LMUs. For example, suppose that the distance from U_1 to the BTS is s_1 , and the distance from U_2 to the BTS is s_2 . U_1 measures time offset Δt_1 and U_2 measures Δt_2 , given by

$$\Delta t_1 = s_1/\nu + \alpha + \varepsilon_{21} ,$$

$$\Delta t_2 = s_2/\nu + \alpha + \varepsilon_{22} , \quad (5)$$

5

where α is the time offset of the BTS transmissions, and ε_{21} and ε_{22} are the time offsets of the LMU internal clocks in U_1 and U_2 respectively. Subtracting the second equation from the first yields

$$\varepsilon_{21} - \varepsilon_{22} = \Delta t_1 - \Delta t_2 + s_1/\nu - s_2/\nu , \quad (6)$$

10

which is the relative time offset of the clock in U_1 with respect to that in U_2 . This process may be repeated for a second pair of LMUs, say U_2 and U_3 , and another BTS whose signals can be received by both members of this second pair of LMUs. In this way a synchronisation map may be calculated, which provides the clock offsets of all the LMU internal clocks relative to one of them adopted as a master 'LMU network clock time'. Having established the LMU synchronisation map in this fashion, a CURSOR position measurement can then include any number of LMUs without the penalty of adding an extra unknown time offset for every LMU, since the relative LMU time offsets are known.

15

20

The receivers discussed in the preceding paragraphs make measurements of time offsets. More generally, receivers can measure time offsets, phase offsets (which can be converted into time offsets with a modulo 360° ambiguity), frequency offsets or rates of change of frequency offsets. Though these measurements are of different quantities, the present invention is applied usefully to each of them as, when combined with similar measurements made by a second receiver, they can independently provide positional information. Positioning systems making use of these measurements are discussed in a related patent application (our reference MJB06427WO) filed simultaneously herewith.

25

30

The present invention teaches how the same advantages of an (effectively) synchronised LMU network may be obtained by setting up one or more 'virtual LMUs' in the network which act as interface nodes for the real LMUs.

5 According to a first aspect of the invention, there is provided a method of generating a list of offsets in time, phase, frequency, or derivatives thereof, or their equivalents expressed as offsets in distance or derivatives thereof, of a plurality of transmission source signals, received at a given location, relative to a common reference, the method comprising

- 10 (a) acquiring data from one or more receivers, the positions of which may be known or determined, the data from a receiver comprising offsets in time, phase, frequency, or derivatives thereof respectively of signals received from the transmission sources relative to a reference source in each receiver or to each other; and
- 15 (b) combining the acquired data and calculating the list of offsets relative to the common reference.

In practice the offsets from the list can be used in place of offsets obtained directly from the receiver or receivers.

20

The relative offsets in time, phase, frequency, or derivatives thereof, with respect to each other or with respect to a reference source, of the signals received by a first receiver from a plurality of the transmission sources may be represented by corresponding offsets or differences in the distances between the transmission sources and the first or second receivers.

25

The invention also includes apparatus using the method above, the apparatus comprising

- 30 (a) means for acquiring data from one or more receivers, the positions of which may be known or determined, the data from a receiver comprising offsets in time, phase, frequency, or derivatives thereof respectively of signals received from the transmission sources relative to a reference source in each receiver or to each other; and

- (b) means for combining the acquired data and calculating the list of offsets relative to the common reference.

In a method using techniques similar to or as described in EP-A-0 880 712, in place of offsets in time, phase, frequency, or derivatives thereof, or their equivalents expressed as offsets in distance or derivatives thereof, data representative of the received signals may be used, from which the offsets of signals received from the transmission sources relative to the reference source may be determined.

Therefore, the invention also includes a method of generating a list of offsets in time, phase, frequency, or derivatives thereof, or their equivalents expressed as offsets in distance or derivatives thereof, of a plurality of transmission source signals, received at a given location, relative to a common reference, the method comprising

- (a) acquiring data from one or more receivers, the positions of which may be known or determined, the data from a receiver being representative of the received signals;
- (b) determining from the acquired data the offsets in time, phase, frequency, or derivatives thereof respectively of signals received from the transmission sources relative to a reference source or to each other; and
- (c) combining the offsets so determined and calculating the list of offsets relative to the common reference.

The invention also includes apparatus for carrying out the method described immediately above, the apparatus comprising

- (a) means for acquiring data from one or more receivers, the positions of which may be known or determined, the data from a receiver being representative of the received signals;
- (b) means for determining from the acquired data the offsets in time, phase, frequency, or derivatives thereof respectively of signals received from the transmission sources relative to a reference source or to each other; and
- (c) means for combining the offsets so determined and calculating the list of offsets relative to the common reference.

A radio positioning method and system including either of the methods and apparatus defined above also form part of the present invention.

5 The invention also includes apparatus (a 'virtual LMU') for carrying out either or both of these methods. The apparatus may include a computer (located anywhere convenient) and programmed to carry out the required process. Although the following description of a particular application of the invention concerns signals in a digital telephone network, it will be apparent that the invention is by no means
10 restricted to this application but may be applied to any network of one or more transmitters, synchronised or unsynchronised, set up for any purpose.

A virtual LMU includes a computer process which may run on any computer platform able to obtain data from real LMUs. Accordingly, a further aspect of the invention
15 includes a method of calculating and maintaining a list of offsets in time, phase, frequency, or derivatives thereof, or their equivalents expressed as offsets in distance or derivatives thereof, of a plurality of transmission source signals, received at a given location, relative to a common reference.

20 It is assumed that the network of BTSs is *unsynchronised* in that the transmission time offsets of the BTS signals bear no constant or known relationship to each other, but that nevertheless the BTS oscillators are quite *stable*, so that their instantaneous frequencies change only slowly with time. In these circumstances, it is possible to predict the currently received offset in time, phase, frequency, or derivatives thereof of
25 the signals from a given BTS by a given real LMU from sufficiently-recent historical data. The real LMUs in the network make measurements of all the BTSs they can detect in a cyclic fashion, repeating the cycle every few seconds. They maintain these measurements in a stack, replacing the oldest measurements with the most recent. A linear or low-order polynomial fit to the measurements therefore provides a predictor
30 for extrapolation into the near future, or for interpolation in the recent past. Assume that the BTS oscillators are sufficiently stable that reliable predictions can be made over a period of, say, ten minutes. Then, every few minutes, the virtual LMU (VLMU) contacts each real LMU and receives its predictors for the received offsets of the signals from all the BTSs in its measurement set. It is likely that many of the

5 BTSs will have been measured by more than one LMU, so the VLMU analyses the complete data set from all the real LMUs using well-known methods to determine both (a) the best values of the real LMU internal clock offsets in time, phase, frequency, or derivatives thereof, and hence (b) the received offsets in time, phase, frequency, or derivatives thereof of the signals from all the BTSs which would have been measured by a real LMU located at the assumed position of the VLMU and capable of receiving signals from every BTS.

10 In the above description of the function of the VLMU, it should be understood that any or all of the LMUs could be replaced by other receivers, not necessarily fixed or at known positions, which have not been set up specifically as LMUs. For example, the data from a number of handsets could be used to determine frequency offsets if the handsets were stationary. Furthermore, it is shown in a related patent application (our reference MJB06427WO) filed simultaneously herewith, how the positions and
15 velocities of handsets can be determined without the need for any LMUs at all.

Particular advantages of using a VLMU in a network include the following:

- (a) a full match can be guaranteed between a handset's measurements and a single (virtual) LMU;
- 20 (b) the VLMU process minimises the timing errors in individual LMU measurements;
- (c) the VLMU list is immediately available to the position calculation process, increasing the speed of computation;
- (d) when combined with the ideas described in a related patent application (our reference MJB06427WO) filed simultaneously herewith, a list of receive time
25 offsets can be created in a network of BTSs where there are few if any real LMUs;
- (e) the VLMU provides, in effect, a synchronisation map of the real LMU network which network may then be used to monitor the BTS network and, in particular, to determine locations of newly-installed BTSs.

30 One example of a method and apparatus according to the present invention will now be described with reference to the accompanying drawings, in which:

Figure 1 shows the geometry of a CURSOR system as described in EP-A-0 880 712;

Figure 2 shows adjacent LMUs making measurements of a common BTS;

Figure 3 shows a network of real and virtual LMUs in a system of the invention;

5 Figure 4 illustrates a similar, simplified network;

Figure 5 shows the positions of LMU sites and BTS sites in a real network;

Figure 6 shows the same network with the addition of a Virtual LMU;

10

Figure 7 shows the same network with the real LMUs replaced by the Virtual LMU;

Figure 8 illustrates, by way of a flow chart, the processing which takes place inside an LMU;

15

Figure 9 illustrates, by way of a flow chart, the processing which takes place inside the VLMU;

Figure 10 shows a list of timing offsets generated in a real system such as that shown in the example of Figures 5 to 9; and

20

Figure 11 shows a table of timing errors associated with LMUs and a virtual LMU in this example.

25 By way of example, and with reference to Figure 3, the function of a virtual LMU is now described which determines timing offsets.

Consider a network of N real LMUs and M BTSs which includes a virtual LMU (VLMU). The position of the n^{th} LMU, U_n , is represented by the vector \mathbf{u}_n and the position of the m^{th} BTS, B_m , is represented by the vector \mathbf{b}_m , both vectors being with respect to the same origin. Signals radiated by BTS m will be received by LMU n after a time lag, and the measurement of this time lag, Δt_{nm} , is given by

30

$$\Delta t_{nm} = |\mathbf{u}_n - \mathbf{b}_m|/c + \varepsilon_n + \alpha_m \pm \sigma_{nm}, \quad (7)$$

where ε_n is the clock time offset of LMU n , α_m is the transmission time offset of BTS m , both with respect to an imaginary universal 'absolute' clock, and σ_{nm} is an estimate of the error in the measurement of Δt_{nm} . The assumed position of the virtual LMU, V , is represented by the vector \mathbf{v} . If the VLMU were able to receive the signals directly from BTS m without error then it would measure a receive time offset, β_m , relative to the imaginary universal absolute clock, given by

$$\beta_m = |\mathbf{v} - \mathbf{b}_m|/c + \alpha_m. \quad (8)$$

Substituting for α_m in equation (7) using the value deduced from equation (8) gives

$$\Delta t_{nm} = |\mathbf{u}_n - \mathbf{b}_m|/c + \varepsilon_n + \beta_m - |\mathbf{v} - \mathbf{b}_m|/c \pm \sigma_{nm}. \quad (9)$$

Over the entire network of N LMUs, all of the M BTSs are visible. Each individual LMU, however, will only see a few of them, but as long as there is significant overlap of visibility, it is possible to take the set of all Δt values and solve for values of ε_n and β_m . Hence the VLMU can calculate timings for any BTS as if the network of LMUs were synchronised, or as if just one LMU (the VLMU, V) was all that was needed to cover the entire BTS network.

To illustrate this further, a simplified problem is shown and solved below using $N = 2$ and $M = 4$, i.e. a network consisting of just 2 LMUs monitoring 4 BTSs (see Figure 4). For simplicity it is chosen that $\varepsilon_1 = 0$. This is allowed as the 'absolute' clock time is completely arbitrary and may, for example, be measured by the internal clock of LMU number one. (Note, however, that this choice does introduce an asymmetry into the solution in that the error associated with BTSs three and four are not the same.) The first LMU (U_1) can receive signals from BTS numbers one, two and three, but cannot receive the signals from BTS number four. The second LMU (U_2) can receive the signals from BTSs one, two and four, but cannot see BTS number three. The equations can be written in matrix form as

$$\begin{pmatrix} 1 & 0 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 & 0 \\ 0 & 0 & 1 & 0 & 0 \\ 1 & 0 & 0 & 0 & 1 \\ 0 & 1 & 0 & 0 & 1 \\ 0 & 0 & 0 & 1 & 1 \end{pmatrix} \begin{pmatrix} \beta_1 \\ \beta_2 \\ \beta_3 \\ \beta_4 \\ \varepsilon_2 \end{pmatrix} = \begin{pmatrix} \Delta t_{11} - \frac{|\mathbf{u}_1 - \mathbf{b}_1| - |\mathbf{v} - \mathbf{b}_1|}{v} \\ \Delta t_{12} - \frac{|\mathbf{u}_1 - \mathbf{b}_2| - |\mathbf{v} - \mathbf{b}_2|}{v} \\ \Delta t_{13} - \frac{|\mathbf{u}_1 - \mathbf{b}_3| - |\mathbf{v} - \mathbf{b}_3|}{v} \\ \Delta t_{21} - \frac{|\mathbf{u}_2 - \mathbf{b}_1| - |\mathbf{v} - \mathbf{b}_1|}{v} \\ \Delta t_{22} - \frac{|\mathbf{u}_2 - \mathbf{b}_2| - |\mathbf{v} - \mathbf{b}_2|}{v} \\ \Delta t_{24} - \frac{|\mathbf{u}_2 - \mathbf{b}_4| - |\mathbf{v} - \mathbf{b}_4|}{v} \end{pmatrix} + \mathbf{Z} \quad (10)$$

or equivalently as $\mathbf{A}\mathbf{x} = \mathbf{b} + \mathbf{Z}$, where \mathbf{Z} is an unknown vector of the actual errors on each measurement.

5

The standard technique known as ‘least squares’ postulates that the estimate for \mathbf{x} which minimises \mathbf{Z} is given by

$$\mathbf{x} = (\mathbf{A}^T \mathbf{W} \mathbf{A})^{-1} \mathbf{A}^T \mathbf{W} \mathbf{b}, \quad (11)$$

10

where the symbol \mathbf{A}^T indicates the transpose of the matrix \mathbf{A} , and the matrix \mathbf{W} is defined by

$$\mathbf{W} = \begin{pmatrix} \frac{1}{\sigma_{11}^2} & 0 & 0 & 0 & 0 & 0 \\ 0 & \frac{1}{\sigma_{12}^2} & 0 & 0 & 0 & 0 \\ 0 & 0 & \frac{1}{\sigma_{13}^2} & 0 & 0 & 0 \\ 0 & 0 & 0 & \frac{1}{\sigma_{21}^2} & 0 & 0 \\ 0 & 0 & 0 & 0 & \frac{1}{\sigma_{22}^2} & 0 \\ 0 & 0 & 0 & 0 & 0 & \frac{1}{\sigma_{24}^2} \end{pmatrix}. \quad (12)$$

15

This particular example can be solved explicitly. For simplicity, it is assumed that all the values of σ_{nm} are the same, and equal to σ . This gives the result

$$\begin{aligned} \beta_1 &= (3D_{11} + D_{12} + D_{21} - D_{22})/4 & \pm 0.87\sigma, \\ \beta_2 &= (3D_{12} + D_{11} + D_{22} - D_{21})/4 & \pm 0.87\sigma, \end{aligned}$$

$$\begin{aligned}
\beta_3 &= D_{13} & \pm 1.00\sigma, \\
\beta_4 &= (2D_{24} + D_{11} + D_{12} - D_{21} - D_{22})/2 & \pm 1.41\sigma, \\
\varepsilon_2 &= (D_{21} + D_{22} - D_{11} - D_{12})/2 & \pm 1.00\sigma,
\end{aligned} \tag{13}$$

5 where

$$D_{nm} = \Delta t_{nm} - \frac{|\mathbf{u}_n - \mathbf{b}_m| - |\mathbf{v} - \mathbf{b}_m|}{v}. \tag{14}$$

Note that even in this simple case, when a BTS is seen by both LMUs, the errors in the calculated offsets are less than those in each of the measurements themselves. This is an important advantage of the virtual LMU method.

The LMUs may also contain other means of synchronisation. For example, each real LMU could be connected to a GPS or other timing reference receiver, G, which serves to provide the common timing reference. In this case, the LMU network may be considered as synchronised already to this common timing reference (say GPS standard time), and then the VLMU need not solve for the individual values of ε as these are already known. One advantage of using other means of synchronisation is that there is no longer a requirement for overlap of visibility of BTSs between adjacent LMUs. If each BTS site also carried an LMU, then that LMU would need only to be able to receive the (very strong) signals from its co-sited BTS transmitter(s), thereby simplifying the installation of the LMU antenna.

The VLMU mode of operation described above may be called the ‘pull mode’ as it requires the VLMU to instigate data transfer to itself from every real LMU. It is also possible to have each real LMU continuously check the difference between its own prediction of the receive time offset from every BTS using the values calculated from the set of predictors last sent to the VLMU and the actual measured values. When any one of these differences exceeds a given value, the LMU can send its new predictor set to the VLMU. This mode of operation may be called the ‘push mode’. The particular mode appropriate for a real system depends, amongst other things, on the stability of the BTS network.

An example of a prototype system constructed in accordance with the invention will now be described, in which timing measurements made by a number of LMUs are combined to create a list of receive time offsets for all the GSM BTSs in and around Cambridge, UK, as if they were observed by a single "Virtual" LMU.

5

The positions of nine LMUs, $U_1 - U_9$ (shown as filled circles) and twenty three Cambridge area BTSs, $B_1 - B_{23}$ (shown by unfilled squares) are plotted in Figure 5 on an Ordinance Survey (OS) grid. Each LMU comprises (a) hardware including an internal clock, a GSM radio, a computer, and a telephone connection, and (b) software including a program to compile a list of receive time offsets.

10

Figure 8 illustrates, by way of a flow chart, the main elements of the LMU software residing in each LMU, $U_1 - U_9$. Every few seconds the "scan cycle" program is entered at step A1. The program proceeds, in steps A2, A3, A6 and A7, to tune the GSM radio to each GSM transmission channel in turn and scan for BCCH signals. In the event that a BCCH signal is detected in step A3, the program calculates the receive time offset of the signal relative to its internal clock (in step A4) and updates its list of time offsets accordingly in step A5. The BCCH is also decoded to produce the ID of the BTS B_n from which the signal is received. Figure 5 also shows lines between LMUs and the BTSs detected by them as a result of the scan cycle routine.

15

20

Figure 6 shows the positions of the nine LMUs, the twenty three BTSs monitored by those LMUs and a Virtual LMU V (plotted as an unfilled circle). The Virtual LMU V comprises (a) hardware including a telephone connection to each real LMU and a computer, and (b) software including a program to compile a list of "virtual" receive time offsets.

25

Figure 9 illustrates, by way of a flow chart, the main elements of the VLMU software. Every 4 minutes the "VLMU update" program is entered at step V1. The program proceeds, in steps V2, V3, V5 and V6, to connect to each of the real LMUs via the telephone connections. If the connection to a given LMU $U_1 - U_9$ succeeds, the program, in step V4, extracts that LMU's list of receive time offsets. On completion of the connection cycle, the program (in step V7) combines the data to produce a list of receive time offsets for all the BTSs monitored by the LMU network. An example

30

of this list is shown in Figure 10 where part of a table of receive time offsets generated by the VLMU is reproduced. The first column shows the BTS identifier and the figures in the table are in units of 1.85 microseconds. Figure 6 also shows lines between the VLMU V and each real LMU $U_1 - U_9$ from which the VLMU software is able to extract a list of time offsets.

Once the “VLMU update” has been completed, the combined list of timings generated is equivalent to that which would have been observed had there been a single (real) LMU at the VLMU’s location making timing measurements of every BTS in the network. Figure 7 illustrates this equivalence by showing the virtual monitoring of each BTS’s timing measurements by the Virtual LMU (shown as lines between the VLMU V and the BTSs $B_1 - B_{23}$).

Each timing measurement has an associated error which, in most cases, is smaller than the errors in the timing measurements made by the individual real LMUs. This is illustrated in the table of Figure 11, which shows part of the list produced by the VLMU during operation. The first column shows the identifier of each BTS. The columns headed 1 to 9 each relate to a particular one of the nine real LMUs. The figures in the table are errors in the timing measurements made by the real LMUs of the signals from the corresponding BTSs. An empty cell indicates that the LMU is unable to receive a BTS’s signal. The column headed VLMU shows the result of combining the measurements using the method outlined above.

The timings in the table of Figure 11 are in units of 1.85 microseconds. Note that the VLMU timing errors are generally smaller than those estimated for real LMU timings, confirming an advantage of the VLMU method in reducing errors.

CLAIMS

1. A method of generating a list of offsets in time, phase, frequency, or
5 derivatives thereof, or their equivalents expressed as offsets in distance or derivatives
thereof, of a plurality of transmission source signals, received at a given location,
relative to a common reference, the method comprising
- (a) acquiring data from one or more receivers, the positions of which may
10 be known or determined, the data from a receiver comprising offsets in time,
phase, frequency, or derivatives thereof, respectively of signals received from
the transmission sources relative to a reference source in each receiver or to
each other; and
 - (b) combining the acquired data and calculating the list of offsets relative
15 to the common reference.
2. A method of generating a list of offsets in time, phase, frequency, or
derivatives thereof, or their equivalents expressed as offsets in distance or derivatives
thereof, of a plurality of transmission source signals, received at a given location,
relative to a common reference, the method comprising
- 20 (a) acquiring data from one or more receivers, the positions of which may
be known or determined, the data from a receiver being representative of the
received signals;
 - (b) determining from the acquired data the offsets in time, phase,
frequency, or derivatives thereof, respectively of signals received from the
25 transmission sources relative to a reference source or to each other; and
 - (c) combining the offsets so determined and calculating the list of offsets
relative to the common reference.
3. A radio positioning method for determining the position of one or more
30 receivers the positions of which are unknown, which method includes the method of
claim 1 or claim 2.
4. A radio positioning method according to claim 3, wherein the common
reference comprises an external reference.

5. A radio positioning method according to claim 4, wherein the common reference comprises a GPS signal.

5 6. A radio positioning method according to any of claims 3 to 5, wherein the step of acquiring data from said one or more receivers includes instigating acquisition of said data from a common location.

7. A radio positioning method according to any of claims 3 to 5, wherein the step
10 of acquiring data from said one or more receivers includes instigating acquisition of said data from each said receiver at times determined by each said receiver.

8. Apparatus for generating a list of offsets in time, phase, frequency, or derivatives thereof, or their equivalents expressed as offsets in distance or derivatives
15 thereof, of a plurality of transmission source signals, received at a given location, relative to a common reference, the apparatus comprising

(a) means for acquiring data from one or more receivers, the positions of which may be known or determined, the data from a receiver comprising offsets in time, phase, frequency, or derivatives thereof, respectively of signals
20 received from the transmission sources relative to a reference source in each receiver or to each other; and

(b) means for combining the acquired data and calculating the list of offsets relative to the common reference.

9. Apparatus for generating a list of offsets in time, phase, frequency, or derivatives thereof, or their equivalents expressed as offsets in distance or derivatives thereof, of a plurality of transmission source signals, received at a given location, relative to a common reference, the apparatus comprising

(a) means for acquiring data from one or more receivers, the positions of which may be known or determined, the data from a receiver being representative of the received signals;
30

(b) means for determining from the acquired data the offsets in time, phase, frequency, or derivatives thereof, respectively of signals received from the transmission sources relative to a reference source or to each other; and

(c) means for combining the offsets so determined and calculating the list of offsets relative to the common reference.

10. A radio positioning system including apparatus according to claim 8 or to
5 claim 9.

11. A radio positioning system according to claim 10, wherein the common reference comprises a reference external to said receivers.

10 12. A radio positioning system according to claim 11, wherein the common reference comprises a GPS signal.

13. A radio positioning system according to any of claims 10 to 12, wherein the means for acquiring data from said one or more receivers includes a computer system
15 arranged to instigate the transfer of said data from said one or more receivers to said computer system at times determined by said computer system.

14. A radio positioning system according to any of claims 10 to 13, wherein the means for acquiring data from said one or more receivers includes a computer system,
20 and including means for instigating said acquisition of data from each said receiver at times determined by each said receiver.

15. A digital telephone network, including a radio positioning system according to any of claims 10 to 14.

IMPROVEMENTS IN RADIO POSITIONING SYSTEMS

ABSTRACT

- 5 The invention described relates to a radio positioning system primarily for a mobile telephone network, in which a list of offsets in time, phase, frequency, or derivatives thereof, or their equivalents expressed as offsets in distance or derivatives thereof, of a plurality of transmission source signals, received at a given location, relative to a common reference are generated. Data is acquired from one or more receivers, the
- 10 positions of which may be known or determined. Such data are offsets in time, phase, frequency, or derivatives thereof, respectively of signals received from the transmission sources relative to a reference source in each receiver or to each other. The acquired data is combined for calculating the list of offsets relative to the common reference.




Figure 1




Figure 2




Figure 3




Figure 4

09/830447




Figure 5




Figure 6

09/830447




Figure 7




Figure 8




Figure 9

BTS identifier	VLMU receive time offsets
1727	1959.950
1728	75.364
1733	604.57
17332	165.1479
17333	797.851
17342	797.813
17343	2072.920
18072	182.409
18073	1686.043
33060	1028.109
33070	1061.910
42140	1453.715
55440	1343.821
55500	60.012
55512	2026.607
55513	1690.698
55513	1772.834
55513	2221.130

Figure 10

LMU number	1	2	3	4	5	6	7	8	9	VLMU
BTS identifier										
1727					0.098	0.168				0.101
1728	0.091				0.136	0.076		0.071		0.048
1733				0.159						0.099
17332					0.093			0.087		0.101
17333										0.083
17342	0.087	0.163	0.061			0.074	0.049	0.055	0.084	0.055
17343				0.044			0.047			0.031
18072		0.048	0.086							0.041
18073		0.125							0.089	0.050
33060			0.045	0.047			0.036			0.129
33070		0.050	0.033						0.138	0.033
42140		0.053	0.084			0.171			0.055	0.040
55440	0.056									0.045
55500			0.058	0.066	0.138	0.046	0.067			0.069
55512				0.048		0.038	0.039			0.033
55513				0.047			0.058		0.078	0.032
					0.146				0.096	0.040
									0.055	0.15

Figure 11

DECLARATION AND POWER OF ATTORNEY

As a below-named inventor, I hereby declare that my residence, post office address and citizenship are as stated below next to my name; I believe I am the original, first and sole inventor (if only one name is listed below) or an original, first and joint inventor (if plural names are listed below) of subject matter which is claimed and for which a patent is sought on an invention entitled
IMPROVEMENTS IN RADIO POSITIONING SYSTEMS

the specification of which ☐ is attached hereto or

☒ was filed on 01 JUN 2000 as United States Application Number or PCT International Application Number PCT/GB00/02104 and was amended on (if applicable)

I hereby state that I have reviewed and understand the contents of the above identified specification, including the claims, as amended by any amendment referred to above. I acknowledge the duty to disclose information which is material to patentability as defined in 37 CFR 1.56. I hereby claim foreign priority benefits under 35 U.S.C. 119(a)-(d) or 365(b) of any foreign application(s) for patent or inventor's certificate, or 365(a) of any PCT international application which designated at least one country other than the United States of America, listed below and have also identified below, by checking the box, any foreign application for a patent or inventor's certificate, or PCT international application having a filing date before that of the application on which priority is claimed:

Prior Foreign Application Number(s)	Country	Foreign Filing Date	Priority Not Claimed	Certified Copy Attached?	
				YES	NO
9912724.3	GB	01 JUN 1999	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
			<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
			<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>

As a named inventor, I hereby appoint the following registered practitioner(s) to prosecute this application and to transact all business in the Patent and Trademark Office connected therewith:
 David S. Abrams, Reg. No. 22,576; Robert H. Berdo Reg. No. 19,415; Alfred N. Goodman, Reg. No. 26,458; Mark S. Bicks, Reg. No. 28,770; Darle M. Short, Reg. No. 29,213; Frank E. Robbins, Reg. No. 17,729; John E. Holmes, Reg. No. 29,392; David L. Tamoff, Reg. No. 32,383; Garrett V. Davis, Reg. No. 32,023; Stacey J. Longanecker, Reg. No. 33,952; Beatrice N. Robbins, Reg. No. 30,584 and Julie R. Keller Reg. No. 30,488

Direct all correspondence to:

Roylance, Abrams, Berdo & Goodman

1225 Connecticut Avenue, N.W.

Washington, D.C. 20036-2680

USA

TO 240 440360

12

I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under 18 U.S.C 1001 and that such willful false statements may jeopardise the validity of the application or any patent issued thereon.

Full name of sole or First Inventor Peter James DUFFETT-SMITH

Inventor's signature Peter James Duffett Smith

Residence address Cambridge, United Kingdom GBX

Post Office address
41 Denmark Road, Cottenham, Cambridge CB4 8QS, United Kingdom

Country of Citizenship United Kingdom Date of signature 12/Feb/2001

Full name of Second Inventor James Paul BRICE

Inventor's signature James Paul Brice

Residence address Cambridge, United Kingdom GBX

Post Office address
4 Brampton Road, Cambridge CB1 3HL, United Kingdom

Country of Citizenship United Kingdom Date of signature 12/Feb/2001

Full name of Third Inventor Paul HANSEN

Inventor's signature P. Hansen

Residence address Cambridge, United Kingdom GBX

Post Office address
2 Providence Close, Somersham, Cambridge ^{PA} ~~PWE~~17 3YR, United Kingdom

Country of Citizenship United Kingdom Date of signature 12/02/2001